

SL-D800BT

CD/Streaming Music System



**Easy to set up, great to listen to, huge fun to watch!
CD/Bluetooth® Speaker System with Instant Pairing.**

■ **Main Features**

- Bluetooth® Wireless Streaming with Instant Pairing
- Liquid Crystal Display with Graphical Animation
- Independent Internal Speaker enclosure with Bass-reflex port for Left and Right Channels
- Top-loading CD Player that supports MP3/WMA files
- Auxiliary USB Port for USB Charging



Brand	TEAC				
Series	Compact Audio				
Model	SL-D800BT-R (Red)	SL-D800BT-B (Black)	SL-D800BT-W (White)	SL-D800BT-S (Silver)	SL-D800BT-P (Pink)
UPC Code	043774031078	043774031085	043774031092	043774031108	043774031122
EAN Code	4907034218998	4907034 219001	4907034219018	4907034219025	4907034219049
Announcement Date	End of August 2014				
Estimated Delivery Date	End of August 2014				
Overall Dimensions/NW W x H x D	219 x 182 x 179 / 2.5 (mm/kg) 11.5 x 7.2 x 7.1 / 5.5 (inch/lbs)				
Package Dimensions/GW W x H x D	335 x 260 x 215 / 3.7 (mm/kg) 13.2 x 10.2 x 8.5 / 8.2 (inch/lbs)				
Qty. per Master Carton	2 pcs.				

Supplementary New Product Information (SNPI)

The SL-D800BT incorporates state-of-the-art technologies in a compact cabinet. An Instant-Pairing-compatible smartphone can be connected wirelessly and instantly, just by touching the device with the SL-D800BT. Users will also be impressed by a Liquid Crystal display with animated motion graphics.

Stunning bass-rich sound is delivered from 3" speaker unit that's installed in an individual speaker box with rear bass-reflex port. MP3 and WMA files can be played back via a CD player which is located on top of the unit, while there's memory capacity for up to 40 of your favourite radio stations to be stored (20 for AM, another 20 for FM) Furthermore, an auxiliary USB port delivers DC 5V power to USB devices.

● Easy to set up, great to listen to

● Instant Pairing makes wireless pairing as easy as 1-2-3

With an Instant-Pairing-compatible smartphone, you can establish a Bluetooth® wireless connection just by touching the top of the SL-D800BT with your smartphone. Even if your smartphone or portable music player is not Instant-Pairing-compatible, you can still establish a Bluetooth® wireless connection with the conventional pairing process.



**This product does not send audio signals to Bluetooth® headphones/headsets.*

● CD Player supports MP3/WMA files

Top-loading CD player supports MP3/WMA discs, as well as conventional audio CDs. Repeat, Shuffle, Intro and up to 32-track Program play are all provided.



● AM/FM Tuner, and Wake-up timer

Radio fans are catered for by a PLL Synthesized AM/FM Tuner with 20 FM and 20 AM preset memories.

The Wake-up timer allows you to wake up to your favourite CD, or AM/FM stations and there's also a useful sleep timer (up to 90 minutes).

● Multi function LC-display with motion graphics

When you operate the SL-D800BT, tune into a radio station, play back a CD, or change volume, you'll see unique motion graphics on the CD-display.



● 3" Speaker Units for excellent bass

An Independent Internal Speaker enclosure, with Bass-reflex port for Left and Right Channels, helps deliver a superb bass response.

For user convenience, bass and treble tone controls are also provided.

● Auxiliary DC power supply from USB Port

The SL-D800BT incorporates a USB port that delivers 5V DC power for charging, even when the SL-D800BT is in standby mode, so you can charge a USB device while you sleep. (Maximum power supply: 500mA)



** Please note this USB port supplies DC 5V power only. You cannot playback MP3/WMA files on USB Flash Memory, nor play back music from iPod via USB Cable. Your smartphones can be charged via this USB port, though it will take longer than if you charge it with purpose-designed charger.*

Supplementary New Product Information (SNPI)

■ Features at-a-glance

- Bluetooth® Wireless Streaming with Instant Pairing
- Liquid crystal Display with Graphical Animation
- Independent Internal Speaker enclosure with Bass-reflex port for Left and Right Channels
- CD Player supports MP3/WMA files
- Repeat (1/All/Folder), Intro, Shuffle Play
- 32-track Program Play
- USB Port for USB Charging (Power Supply: 500mA)
- AM/FM Tuner with 20 AM + 20 FM Presets
- On Timer (Selectable source: CD, FM, AM)
- Sleep Timer (up to 90 minutes)
- Bass and Treble Tone Controls
- Muting
- Remote Control
- Complies with RoHS

■ Specifications

CD section

Supported Disc:	CD-DA, CD-R, CD-RW
Supported Formats:	PCM (CD-DA), MP3, WMA
PCM	
Sampling Frequency:	44.1kHz
Bit-length:	16-bit
MP3	
Sampling Frequency:	16k to 48kHz
Bit-rate:	8k to 320kbps
File Extension:	.mp3
WMA	
Sampling Frequency:	32k, 44.1k, 48kHz
Bit-rate:	8k to 320kbps
File Extension:	.wma
DRM not supported	
Maximum Number of Folders:	99
Maximum Number of Files:	999
Frequency Response:	20 to 20kHz
Signal-to-Noise Ratio :	more than 70dB

Bluetooth® section

Bluetooth® Version:	3.0
Bluetooth® Class:	Class 2 (Range: approx. 10m/33ft.)
Supported Profile:	A2DP, AVRCP
Codec:	SBC

Tuner section

Band:	AM, FM
FM Range:	87.50 MHz to 108.00 MHz
AM Range:	530kHz to 1,710kHz (US/Canada), 522kHz to 1,629kHz (UK/Europe)
Number of Preset Stations:	FM 20, AM 20

USB section

USB Port:	USB A (Power Supply Only)
DC Supply:	500mA

**Playing back MP3/WMA files from USB Flash Memory is not supported.*

Timer section

Timer:	On Timer
Sleep Timer:	90, 75, 60, 45, 30, or 15 minutes

General

Speakers:	Full-range, Rear Bass-reflex
Units:	3 inch Cone x 2
Output Power:	5W + 5W
Power:	AC 100-240V 50/60Hz

Last Updated on: September 2, 2014

TEAC

Supplementary New Product Information (SNPI)

Power Consumption:	18W
Dimensions (W x H x D):	291 x 182 x 179 mm, 11.5" x 7.2" x 7.1"
Weight:	2.5 kg, 5.5 lbs.
Accessories:	AC Adapter (PS-M0926), Remote Control (RC-1317), Battery (CR2032), AM Loop Antenna, Owner's Manual, Warranty Card

■ Rear and Side Panels

